

TOS6210

Ground Bond Tester

Ground Bond tester supporting standard compliance tests up to 60A



TOS6210

GPIB **RS232C** **DRIVERS** **CE** **UK** **CA**

Test up to 60 A is possible!

While inheriting the basic performance and functions of its predecessor (TOS6200), such as a constant current driving system that provides current waveforms with little skew and high measurement accuracy, the TOS6210 tester extends the maximum test current from 30 A to 60 A, which is demanded by the new standard. In addition, the tester also lets you judge the acceptability of the device under test based on the drop in voltage, as required in the standard. What's more, you can preset test conditions of up to 20 different types of safety standards, such as those for information technology equipment, home appliances, medical devices, and measuring instruments, in the memory on the main unit's panel.

A simple memory call operation allows you to set up a protective earth or protective bonding continuity test as stipulated in UL and other relevant specifications including IEC and JIS standards. The tester also features a set of functions that meet the specific needs of testing personnel, such as an offset cancellation function and a memo function that allows you to input calibration dates, production numbers, and other test-related information and read the input information later via the GPIB or RS232C interface.

- Test current value: 6 A to 60 A AC / Resistance value: 0.001 Ω to 0.600 Ω
- Voltage drop-based judgment function
- Offset cancelling function
- Stores 100 test conditions in memory
- Incorporates test conditions into program
- Contact check function
- Equipped with standard GPIB and RS232C interfaces
- Equipped with standard test lead (TL12-TOS)

| Output block | | |
|---------------------------------------|--|--|
| Current setting range *1, *4 | | 6.0 to 62.0 A AC (With respect to resistance resulting in output power of the maximum rated Output or less and an output terminal voltage of 5.4 V or less) |
| | Resolution | 0.1A |
| | Accuracy | ± (1% of setting + 0.4A) |
| Maximum rated output | | 220 VA (at the output terminals) |
| Distortion factor | | 2% or less (with respect to 0.1 Ω pure resistance load of 20 A or greater) |
| Frequency | | 50/60 Hz, sine wave (selectable) |
| | Accuracy | ±200ppm |
| Open terminal voltage | | 6 Vrms or less |
| Output method | | PWM switching method |
| Output ammeter | | |
| Measurement range | | 0.0 to 66.0 A AC |
| | Resolution | 0.1A |
| | Accuracy | ± (1% of reading + 0.4A) |
| Response | | Mean value response/rms value display (response time: 200 ms) |
| Holding function | | The current measured at the end of test is held during the PASS or FAIL interval |
| Output voltmeter | | |
| Measurement range | | 0.00 to 6.00 V AC |
| | Resolution | 0.01V |
| Offset cancel function | | 0.00 to 5.40 V (Offset ON/OFF function provided) |
| | Accuracy | ± (1% of reading + 0.02V) |
| Response | | Mean value response/rms value display (response time: 200 ms) |
| Holding function | | The voltage measured at the end of test is held during the PASS or FAIL interval |
| Ohmmeter *2 | | |
| Measurement range | | 0.001 to 0.600 Ω |
| | Resolution | 0.001 Ω |
| Offset cancel function | | 0.000 to 0.600 Ω (Offset ON/OFF function provided) |
| | Accuracy | ± (2% of reading + 0.003 Ω) |
| Holding function | | The resistance measured at the end of test is held during the PASS or FAIL interval |
| Pass/fail judgement function *3 | | |
| Resistance value-based judgement | | Window comparator system •If a resistance value equal to or greater than the upper reference value is detected, a FAIL determination is returned. •If a resistance value equal to or less than the lower reference value is detected, a FAIL determination is returned. •If a resistance value has been judged as FAIL, the tester shuts off the output and generates a FAIL signal. •If the set time elapses without abnormalities, the tester shuts off the output and generates a PASS signal. |
| | Setting range for the upper reference value (UPPER) | 0.001 to 0.600 Ω |
| | Setting range for the lower reference value (LOWER) | 0.001 to 0.600 Ω |
| | Resolution | 0.001 Ω |
| | Judgement accuracy | ± (2% of UPPER + 0.003 Ω) |
| Sampled voltage value-based judgement | | Window comparator system •If a voltage value equal to or greater than the upper reference value is detected, a FAIL determination is returned. •If a voltage value equal to or less than the lower reference value is detected, a FAIL determination is returned. •If a voltage value has been judged as FAIL, the tester shuts off the output and generates a FAIL signal. •If the set time elapses without abnormalities, the tester shuts off the output and generates a PASS signal. |
| | Setting range for the upper reference value (UPPER) *4 | 0.01 to 5.40 V |
| | Setting range for the lower reference value (LOWER) | 0.01 to 5.40 V |
| | Resolution | 0.01 V |
| | Judgement accuracy | ± (2% of UPPER + 0.05 V) |
| Calibration | | Calibration is performed with the rms value of the sine wave, using a pure resistance load. |
| LED | PASS | Lights for approximately 0.2 sec when the measured value has been judged as PASS. It is lit continuously when the PASS holding time is set to HOLD. |
| | UPPER FAIL | Lights if a resistance or voltage value equal to or greater than the upper reference value is detected and judged FAIL. |
| | LOWER FAIL | Lights if a resistance or voltage value equal to or greater than the upper reference value is detected and judged FAIL. |
| Buzzer | | The buzzer sounds for the pass holding time has been set if the measured value has been judged as PASS. The buzzer sounds continuously under the following condition: •The measured value has been judged as PASS when the PASS holding time is set to HOLD. •The measured value has been judged as UPPER FAIL. •The measured value has been judged as LOWER FAIL. The buzzer volume for FAIL or PASS judgment are adjustable. Note that it cannot be adjusted individually since setting is shared with the setting for PASS. |
| Time | | |
| Test time | Setting range | 0.3 to 999 s Timer ON/OFF function is available. |
| | Accuracy | ± (100 ppm of setting + 20 ms) |

*1: Time limitation with respect to output.

The heat radiation capacity at the output block of the tester is designed to be one-third of the rated output, accounting for size, weight, cost, and other factors. Always use the tester within the limitation values given below. Use of the tester beyond these limits will cause the temperature of the output block to rise excessively, potentially tripping the internal protection circuit. In this case, suspend testing for approximately 30 minutes, then press the STOP switch. When temperatures fall to normal levels, the tester will revert to ready status.


| Output time limitation | | | |
|----------------------------|--------------------|--|--|
| Ambient temperature t (°C) | Test current I (A) | Pause time | Maximum allowable continuous test time |
| t ≤ 40° | 40 < I ≤ 60 | Equal to or greater than the test time | ≤ 10 minutes |
| | 20 < I ≤ 40 | Equal to or greater than the test time | ≤ 30 minutes |
| | I ≤ 20 | Not required | Continuous output possible |

*2: About ohmmeter's response time. A resistance value is instantaneously obtained, calculated using the measured voltage and current values. The response time of the ohmmeter complies with the response times of the voltmeter and ammeter.

*3: Resistance value-based and sampled voltage value-based judgments cannot be simultaneously conducted.

*4: Limited by the maximum rated output and the output terminal voltage. The tester can be used within the range shown below.

Allowable range in which to determine the test current value and upper reference value



TOS6210

Ground Bond Tester

| Environment | | |
|---|--------------------|--|
| Operating environment | | Indoor use, Overvoltage Category II |
| Warranty range | Temperature | 5 ° to 35 °C (41 °F to 95 °F) |
| | Humidity | 20 %rh to 80 %rh (non condensing) |
| Operating range | Temperature | 0 ° to 40 °C (32 °F to 104 °F) |
| | Humidity | 20 %rh to 80 %rh (non condensing) |
| Storage range | Temperature | -20 ° to 70 °C (-4 °F to +158 °F) |
| | Humidity | 90 %rh or less (non condensing) |
| Altitude | | Up to 2000 m |
| Power requirement | | |
| Allowable voltage range | | 85 to 250 V AC |
| Power consumption | At no load (READY) | 60 VA or less |
| | At rated load | 420 VA max. |
| Allowable frequency range | | 47 Hz to 63 Hz |
| Insulation resistance | | 30 MΩ min. (500 V DC), between AC line and chassis |
| Hipot | | 1390 V AC (2 seconds), between AC line and chassis |
| Ground bond | | 25 A AC/0.1 Ω max. |
| Safety *5 | | |
| Conforms to the requirements of the following directive and standard. | | |
| Low Voltage Directive 2014/35/EU *6 | | |
| EN61010-1 (Class I *7, Pollution degree 2 *8) | | |
| Electromagnetic compatibility (EMC) *5,*6 | | |
| Conforms to the requirements of the following directive and standard. | | |
| EMC Directive 2014/30/EU | | |
| EN 61326-1 (Class A *9) | | |
| EN 55011 (Class A *9, Group 1 *10) | | |
| EN 61000-3-2 | | |
| EN 61000-3-3 | | |
| Under following conditions | | |
| 1. Used test leadwire (TL12-TOS) | | |
| which is supplied. | | |
| 2. Used the shielded cable which length is less than three meters when the SIGNAL I/O is used. | | |
| Physical dimensions(maximum) / Weight | | |
| 430[16.93 inch] (455[17.91 inch]) W × 88[3.46 inch] (140[5.51 inch]) H × 270[10.63 inch] (350[13.78 inch]) D mm / Approx. 11 kg(Approx.24.25 lbs) | | |
| Accessories | | |
| AC power cord: 1 piece, Test leadwire TL12-TOS: 1 set, Short bar: 2 pieces (These are inserted between the OUTPUT and SAMPLING terminals.), | | |
| AC power fuse: 2 pieces (2, including one spare in the fuse holder), Operation manual: 1 copy | | |

*5: Not applicable to custom order models.

*6: Only on models that have CE/ UKCA marking on the panel.

*7: This instrument is a Class I equipment. Be sure to ground the protective conductor terminal of the instrument. The safety of the instrument is not guaranteed unless the instrument is grounded properly.

*8: Pollution is addition of foreign matter (solid, liquid or gaseous) that may produce a reduction of dielectric strength or surface resistivity. Pollution Degree 2 assumes that only non-conductive pollution will occur except for an occasional temporary conductivity caused by condensation.

*9: This is a Class A equipment. This product is intended for use in an industrial environment. This product may cause interference if used in residential areas. Such use must be avoided unless the user takes special measures to reduce electromagnetic emissions to prevent interference to the reception of radio and television broadcasts.

*10: This is a Group I equipment. This product does not generate and/or use intentionally radio-frequency energy, in the form of electromagnetic radiation, inductive and/or capacitive coupling, for the treatment of material or inspection/ analysis purpose.

— External dimensional diagrams —

